


XLA25 Series Configuration Arrays and Wiring



Model	Output Voltage	Compliance Voltage Range (V)	Recommended n LED(s) per String *	Current POT Adjust Range (A)
	125	87.5 - 131.25	24 - 48	0.2
	106	74.2 - 111.3	20 - 41	0.235
	96	67.2 - 100.8	18 - 37	0.260
	83	58.1 - 87.15	16 - 32	0.3
	71	49.7 - 74.55	13 - 27	0.35
	63	44.1 - 66.15	12 - 24	0.4
	56	39.2 - 58.8	10 - 21	0.45
	50	35 - 52.5	9 - 19	0.5
	38	26.6 - 39.9	7 - 14	0.65
	36	25.2 - 37.8	7 - 14	0.7
	28	19.6 - 29.4	5 - 10	0.9
	24	16.8 - 25.2	4 - 9	1.05
	20	14 - 21	3 - 7	1.25
	17	11.9 - 17.85	3 - 6	1.50
	12	8.4 - 12.6	2 - 4	2.00

* LED Vf range: 2.7-3.6 V

The GRE Alpha logo is a registered trademark of GRE Alpha Electronics Ltd.

All other names are the property of their respective owners

Copyright © 2012 GRE Alpha. All rights reserved. Reproduction in whole or in part without permission is prohibited